



www.hydrofarm.com

HOW TO USE YOUR SUNRISE REFLECTOR HANGING SYSTEM:

- 1.** Most reflectors are supplied with V shaped hangers. If your reflector does not have any hangers, you will need to purchase some from your Hydrofarm dealer. (Item # LGHOOK).
- 2.** Locate a support structure "joist" in the ceiling. Use the supplied J hooks and screw into the supports. Space the hooks approximately sixteen to eighteen inches apart (note: normal ceiling joists are sixteen inches apart).
- 3.** Use the string from the SunRise Reflector Hanging System to tie a knot around both of the V hangers.
- 4.** Now you are ready to hang your reflector. Mount each SunRise reflector hanger to the ceiling by inserting the J hook through the eyehole.
- 5.** The wing nut on the SunRise Reflector Hanging System is for tension adjustment. Proper tension will allow the ability to move the reflector up or down easily.
- 6.** Each reflector hanger will hold a maximum weight of 11 lbs. Two hangers are required for each reflector, so the maximum acceptable weight for a reflector is 22 lbs.



RFSR

Distributed by: HYDROFARM, Inc. • Petaluma, CA U.S.A.